

MOT202T MODEM UDS / Motorola 202T

Industrial grade & temperature hardened, the **Raymar-Telenetics** MOT202T is a pin-for-pin, form, fit, and function replacement for the Motorola / UDS Model RM16M202T



KEY FEATURES

- 2-wire half duplex or 4-wire full duplex private line operation
- 0 to 1200 bps data rate over unconditional lines and 1800 over high quality lines
- Anti-streaming
- Phase coherent, frequency shift keyed (FSK) modulation
- LED indicators
- Front panel rotary switch function selector
- Integral test features
- 12, 24, 48, 125 VDC Power
- 115VAC, 60Hz - 220/240VAC 50 Hz Power

A MUST FOR INDUSTRIAL APPLICATIONS

The **Raymar-Telenetics** MOT202T (Standalone) features built-in diagnostic, anti-streaming, multi-power inputs (115 to 240AC, 12 to 125VDC) and -40°C to +85°C operating range capabilities.

The modem operates over leased or dedicated, loaded or unloaded lines equal to or better than the ITU (formerly CCITT) M.1020/1025 or the Bell 3002 leased line services. It operates over point-to-point or multi-point polled systems and operates in full or half-duplex over 4-wire or 2-wire circuits.

SUPERIOR ERROR DETECTION CAPABILITIES

The MOT202T employs circuitry to prevent data and carrier detect errors over noisy lines. In multi-drop systems it is very common to have noise spikes and other harmful high frequency components caused by carrier turn-offs from other modems on the same line. The modem uses a combination of soft-carrier generation and soft-carrier detection in conjunction with a signal to noise ration (SNR) detector to eliminate errors caused by line noise.

The MOT202T's anti-streaming capability prevents a modem from remaining in the transmit mode when the modem is not actively transmitting data. In addition, the MOT202T allows users to verify transmitted and received data via the diagnostic feature.

DESIGN VERSATILITY

The MOT202T's interchangeable design between the Universal Data Shelf multiple modem enclosure (RM16M series) and the standalone modem enclosure, enables the modem to be directly inserted in the Universal Data Shelf when the optional front panel is attached. Thus, the data-communications facility can easily upgrade from front multiple standalone enclosures to a centralized rack without the expense and trouble of purchasing new modems.

RAYMAR INFORMATION TECHNOLOGY, INC.

7325 Roseville Road
Sacramento, CA 95842
USA

+1-916-783-1951
FAX +1-916-783-1952

sales@raymarinc.com

1-800-695-1951

Tech Support Hotline
1-800-747-1522

www.raymarinc.com

PRODUCT SPECIFICATIONS

Functional Description

GENERAL

| | |
|----------------------------------|---|
| Data Rate: | From 0 to 1800 bps (baud) depending on transmission facility |
| Modulation: | Phase-coherent Frequency shift keying (FSK) |
| Line Impedance: | 600 ohms \pm 10%, transformer coupled and transient protected |
| Operation: | The modem operates at full-duplex or half-duplex over 4-wire lines, or half-duplex only over 2-wire lines. It operates asynchronously. |
| Receive and Transmit Frequencies | Space: 2200 Hz Mark: 1200 Hz Soft Carrier: 900 Hz |
| Timings: | All settings and timings are controlled by jumpers on the modem board. |
| Anti-streaming: | Option to turn transmitter OFF after a selected time, even if Request to Send is on. |
| Test Features: | The modem employs a rotary switch that selects these test options. <ul style="list-style-type: none"> • Data Mode • Self Test • Analog Loopback • Digital Loopback • Test Pattern Transmit |
| Indicators: | The modem has LED indicators for the following interface circuits: RTS, CTS, DCD, RD, TD, TM (Test Mode) and PWR |

RECEIVER

| | |
|--------------------------------------|--|
| Receiver Center Frequency Tolerance: | 1700 Hz \pm 16 Hz |
| Receiver Performance: | The modem receiver will operate with the following performance at 3002/C2 or M1025 lines |
| 1200Bps: | B.E.R. equal to 1×10^{-5} with 12 db signal to noise ratio |
| 1800Bps: | B.E.R. equal to 1×10^{-5} with 18 db signal to noise ratio |
| Carrier Detect Threshold: | The received carrier detect threshold can be configured by the on-board jumper. <i>With jumper option:</i> DCD off \rightarrow on Carrier stronger than -30 dBm OR DCD off \rightarrow on Carrier stronger than -45 dBm Hysteresis: Approximately 2 dB |
| Receiver Dynamic Range: | 0 dBm to - 43 dBm |

TRANSMITTER

| | |
|--------------------------------|---|
| Transmit Frequency Tolerances: | |
| Space frequency: | \pm 0.1% |
| Mark frequency: | \pm 0.1% |
| Soft Carrier frequency: | \pm 0.1% |
| Transmit Levels: | The modem transmit level is selectable from 0 dBm to - 14 dBm in 2 dB steps by the on-board jumper S2 -1 to 8 |

Power Requirements

RACK & STANDALONE

| | |
|-----------|---------------------------|
| AC Power: | 115 VAC 220/240 VAC |
| DC Power: | -12 to 53 VDC +130 VDC |

Environmental Specifications

| | |
|------------------------|--------------------|
| Operating Temperature: | -40° C to +85° C |
| Storage Temperature: | -40° C to +85° C |
| Relative Humidity: | 95% non-condensing |

Interface Specifications

Analog Line Edge Connector:
An 8-pin edge connector located at the backend of the modem board. The four signals routed to and from this RJ45 connector are the analog transmit and receive pairs. Each pair are fully differential signals.

| Pin | Signal | Function |
|-----|--------|--|
| 3 | DTR | Receive Line for four wire systems |
| 4 | DTX | Transmit/Receive Line for two wire systems |
| 5 | DRX | Transmit/Receive Line for two wire systems |
| 6 | DRR | Receive Line for four wire systems |

| | |
|--------------------------|---|
| Maximum Data Rate: | 0 to 1200 bps (baud) over ITU M.1025 or Bell 3002 Basic services 0 to 1800 bps (baud) over ITU M.1020 or Bell 3002 D2 conditioned lines |
| Interface Compatibility: | The modem's line interface (RJ45) is compatible with the Bell Systems/WE 202T specifications and with the ITU V.23 recommendation. The modem's data interface (DB25 Female) is compatible with the RS232C specifications and with the ITU V.24/28 recommendations. |

MOT202T MODEM • UDS / MOTOROLA 202T

POWER EDGE CONNECTOR

A 12-pin edge connector located at the left side of the modem board. This connector supplies the modem board with power from the standalone case or the modem rack. Header H1 is located on top of P1.

| Pin | Voltage | Function | Header H1 Pin |
|-----|------------|------------------------|---------------|
| 10 | + 15 VDC | Transformer 20 VAC | 2 |
| 12 | - 15 VDC | Transformer 20 VAC | 1 |
| 8 | Center Tap | Transformer center tap | 3 & 4 |
| 4 | + 8.5 VDC | Transformer 10 VAC | 6 |
| 6 | +8.5 VDC | Transformer 10 VAC | 5 |
| 2 | GND | Chassis Ground | n.c. |

DIGITAL DATA EDGE CONNECTOR

P2 is a 25-pin edge connector located at the backend of the modem board. The eleven signals routed to and from this connector are the RS232 data interface signals.

| Pin | RS232 circuit | V.24 circuit | Function |
|-----|---------------|--------------|---------------------|
| 1 | AA | 101 | Protective Ground |
| 2 | BA | 103 | Transmitted Data |
| 3 | BB | 104 | Received Data |
| 4 | CA | 105 | Request To Send |
| 5 | CB | 106 | Clear To Send |
| 6 | CC | 107 | Data Set Ready |
| 7 | AB | 102 | Signal Ground |
| 8 | CF | 109 | Data Carrier Detect |
| 9 | --- | --- | + 12 Volt Test only |
| 10 | --- | --- | - 12 Volt Test only |
| 25 | --- | --- | Analog Loopback |

MODEM BOARD SELECTIVE JUMPER OPTIONS

OPERATIONAL SETTINGS

| | |
|--|---|
| Data Carrier Detect Level - 30 dBm - 45 dBm | Turnaround Squelch In Out |
| Transmit Level 0 dBm - 2 dBm - 4 dBm - 6 dBm - 8 dBm - 10 dBm - 12 dBm - 14 dBm | Transmit Carrier RTS Control Constant Carrier |
| Line Connection 2 - wire 4 - wire | Local Copy Squelch No Local Copy Local Copy |
| Chassis GND Option Chassis GND & Signal GND not connected Chassis GND and Signal GND connected together | Test Generator Baud Rate 1 18 37 75 150 |

MODEM TIMING

| | |
|--|--|
| RTS / CTS Delay 8 ms 33 ms 59 ms 219 ms | Soft Carrier Timing No Soft Carrier 8.3 ms 26.6 ms |
| Data Carrier Detect Delay 6 ms 23 ms | Anti-Streaming Time 4 ms 7.6 ms 14 ms 28 ms 56 ms Out |
| Turnaround Squelch Time 83 ms 159.6 ms | |



WARRANTY

Raymar-Telenetics manufactured products are warranted against defects in hardware material and workmanship under normal use for one (1) year from date of original retail purchase. Defective product will be repaired or replaced, determination to be made by Raymar-Telenetics, at no charge. Repaired or replaced products are warranted for 90 days or for original warranty period, whichever is longer. Warranty extends to original end-user only.



Manufactured in the USA by RAYMAR-TELENETICS

Raymar Information Technology, Inc., 7325 Roseville Road, Sacramento, CA 95842
 1-800-695-1951 fax +1-916-783-1952 sales@raymarinc.com www.raymarinc.com
 Service Support Hotline 1-800-747-1522

0070-0119-000 REV C
 08/27/2010

© 2010 Raymar-Telenetics